

Blower Shelf Modification for RGRA-120 from August 1994 through August 1999

Due to a design change of the collector box (spacers added to top and bottom of collector box), all RGRA furnaces from 1994 to in 1999 will have to undergo a blower shelf modification to accept a heat exchanger replacment.



Collector Box Spacer

1. Remove old heat exchanger
2. While looking at the blower shelf locate base angle
3. From the inside of the cabinet, at the edge of the base angle (A), measure 8" (center) and mark, then measure the same way and from same point 16 and 1/4"(center), and mark, using tin snips cut out about aproximately 1/2" long by 5/16" deep notch (half moon shape)
4. Insert new heat exchanger making sure heat exchanger will pass freely into the furnace cabinet
5. If heat exchanger will not pass freely examine the notches and make sure they are deep enough to allow the heat exchanger to pass.
6. Reinsert screws and install components

